

MICROMODULE ENERGY METER

Remotely monitor power consumption of two electric loads with this compact Z-Wave module. You can easily hide it in a electricity box without altering decoration of your premises. Save energy and money with Micromodule Energy Meter.



DESCRIPTION

Zipato Micromodule Energy Meter monitors total electricity consumption of connected appliances and reports it to Zipato or any other Z-Wave enabled controller in real time. Small and compact size allows easy installation in majority of electricity distribution boxes. It supports two loads up to 6000W each (@ 120V).

PRODUCT FEATURES

- Slim, compact remote Z-Wave module measures power parameters of connected device
- Dual power meter function
- Two amper meter clamp are included in the box
- Instant power wattage and Accumulated power consumption KWh report
- Maximum current measure 60A
- New Z-Wave 500 series
- Very low power consumption
- Over-the-air firmware update
- Easy installation

TECHNICAL SPECIFICATION

PROTOCOL

- Z-Wave Plus

OPERATING VOLTAGE

- 100~240VAC

MAXIMUM LOAD

- 6000W X 2 @ 120V

OPERATING TEMPERATURE

- 0°C ~ 40°C

OPERATING HUMIDITY

- 10% TO 85%RH

STORAGE TEMPERATURE RANGE

- -20°C ~ 60°C

FREQUENCY

- ph-pab01.au 921.42 MHz (AU)
- ph-pab01.eu 868.42 MHz (EU)
- ph-pab01.in 865.20 MHz (IN)
- ph-pab01.is 916.02 MHz (IS)
- ph-pab01.ru 869.02 MHz (RU)
- ph-pab01.us 908.42 MHz (USA/Canada)

DIMENSIONS

- Micromodule: 47 x 16 x 40 mm
- Amper clamp: 29 x 30 x 43 mm
- Package: 127 x 115 x 54 mm

WEIGHT

- Micromodule: 21g
- Amper clamp: 86g
- Package weight: 137,3g

REGULATION

- EMC 2004/108/EC, R&TTE 1995/5/EC, LVD 2006/95/EC, FCC Part 15

WARRANTY

- 1 year standard

NOTE: SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT PRIOR NOTICE