make your home smart

RGBW LIGHT BULB

By using Zipato RGBW bulb, customers can control color and intensity of home lights by just using their smartphones

→ DESCRIPTION

Zipato RGBW LED Bulb with dimmer makes home lighting more fun and comfortable. With Zipato RGBW Bulb, you can control color and intensity of home lights from the convenience of your smartphone, or other Z-Wave enabled controller. It has separate warm white, cold white and color LEDs. This allows you to create both colorful light environments and regular white lighting, which is easily customizable from an iOS or Android smartphone. Bulb fits into regular E27 socket and is able to produce light intensity comparable to 60W incandescent bulb by draining just around 6Watts of power!

→ PRODUCT FEATURES

- Thousands of colors available, warm and cold white, adjustable
- 5 color channels Red, Blue, Green, Warm White and Cool White
- Consumes smallamount of power but generates light comparable to 60W incandescent bulb
- Fits into a regular E27 socket

- Once connected to smart home controller, customers can setup colorful lighting to automatically
- Supports Z-Wave wireless protocol
- Available for iOS and Android

TECHNICAL SPECIFICATION

→ PROTOCOL

Z-Wave Plus

→ STANDARD

Physical E27 standard

→ POWER SUPPLY INPUT

100-240VAC. 50/60Hz

→ STANDBY POWER

0.45W

⊖ OPERATING TEMPERATURE

0°C to 40°C (32°F to 104°F)

→ STORAGE TEMPERATURE

-25°C to 70°C (-13°F to 158°F)

OPERATING HUMIDITY

5% to 95% non-condensing

→ DIMENSIONS

62 x 62 x 12 mm

179g

→ PACKAGE DIMENSIONS 68 x 68 x 151 mm

→ PACKAGE WEIGHT

225g



WIRELESS RF MODE FREQUENCY BAND

- 921.42 MHz (AU)
- 868.42 MHz (EU)
- 865.20 MHz (IN)
- 916.02 MHz (IS) 869.02 MHz (RU)
- 908.42 MHz (US)

→ REGULATION

■ 2006/95/EC The Low Voltage Directive, 89/336/EEC The Electromagnetic Compatibility Directive and 1999/5/EC R&TT EC



1 year standard

NOTE: SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT PRIOR NOTICE